

Synerji
ELECTRICAL



LOCALLY MANUFACTURED SA

Reliability You Can Count On, Locally Made.

by
synerji
ELECTRICAL

LED BELL PRESS DIMMERS

INTRODUCTION

The Synerji Bell Press Dimmer provides smooth and reliable dimming control for compatible 230VAC Synerji dimmable lamps. Designed for effortless operation, a single press switches the light on or off, while pressing and holding adjusts brightness to the desired level. For optimal performance, activate the Synerji Compatibility Mode by pressing the switch seven times. Not suitable for use with wire-wound transformers.

BELL PRESS DIMMER 125W

SYN-STSYDIM12

Power Rating: 125W

Current: 0.5A

Ingress Protection: IP20

Maximum Load: 13 × 6.5W Synerji GU10 lamps



Made in South Africa



Number of lamps that can be used per dimmer	6.5w dimmable GU10 lamps	5.5w dimmable Candle lamps	10w dimmable GLS lamps
125W	UP TO 13	UP TO 16	UP TO 9
500W	UP TO 47	UP TO 59	UP TO 23

2 x Presses	7 x Presses	9 x Presses	11 x Presses	13 x Presses	17 x Presses
Turns lamp on to 50% intensity, irrespective of previous state - mostly for use with Shuttle Master Zone Controller (MZO)	Auto setting for Synerji LED's Setting required if flickering of Synerji lamps are encountered. Also to be used if a lower dimmer intensity is required. If the dimmer accepts the setting, the lamps will go to full intensity.	Set the minimum dim level to lower than factory default Tip - first dim to a low intensity. If the dimmer accepts the settings, the lamps will go to full intensity.	Set the minimum dim level to a user selected level If the dimmer accepts the setting, the lamps will go to full intensity.	Reset all settings to factory default Tip - first dim to a low intensity. If the dimmer accepts the settings, the lamps will go to full intensity.	Set the maximum dim level to a user selected level If the dimmer accepts the setting, the lamps will go to minimal intensity.

0.5A AMPS	IP20 RATING	MAX 13x6.5W SYNERJI GU10
---------------------	-----------------------	---------------------------------------

NB - MUST BE INSTALLED BY A QUALIFIED ELECTRICIAN



Branches in:
Pretoria
Tel: 012 804 - 0120
Email: salespt@electrahertz.co.za

Johannesburg
Tel: 011 397 - 1750
Email: salesjp@electrahertz.co.za

www.electrahertz.co.za

E&OE